HIDIZS

Hi-Res AUDIO MQA ESS

XO (S10) Dongle Manual

亲爱的用户，感谢您购买 Hidizs XO 便携解码耳放，一款经过 Hi-Res Audio、MQA 权威认证的小型 HiFi 解码放大器。

XO 内置 2 颗强悍的 ESS 高端 SABRE 系列最新一代 ESS9219C 解码芯片和高精度、低抖动的独立时钟晶振，兼容单端 3.5 和平衡 2.5 输出，支持本地原生硬解 DSD64/128/256，PCM 最高支持 32bit/384kHz，MQA 最高支持 16X 展开，推力强劲而不过分（平衡 195mW+195mW@32Ω/ 单端：78mW+78mW@32Ω），支持 iOS，Android，Windows，Mac OS，iPad OS，即插即用。

独立按键“XO”具有滤波切换和炫彩氛围灯功能，共有多种以上灯光可选择，2 种滤波效果可供切换，无需刷固件便可体验不同声音风格，为你的 HiFi 之旅增添了趣味与酷炫。XO 经由 Hidizs 音频团队精准调校，听感调整细腻微妙，确保纯净通透的声音质量，希望能给您带来愉快的使用体验。

Hidizs 诚挚邀请您加入 Hidizs VIP

只需输入邮箱，便可成为 Hidizs VIP 会员，第一时间获取 Hidizs 的最新活动信息，如新产品发布，促销活动，奖品活动，优惠券等。

注册成功后可即刻获得一张优惠券。

VIP 会员登记：www.hidizs.net/pages/vip

Subscribe for Hidizs membership

如需了解更多相关信息，请关注Hidizs官方微博、Facebook、Instagram、Twitter、TikTok、Head-fi论坛、微信公众号、QQ交流群（33504015），以获取更多信息并参与线上交流。

Hidizs官方网站：www.hidizs.com 或 www.hidizs.net

Facebook Twitter Instagram TikTok Weibo

XO使用说明

安卓系统手机的使用方法

1.通过XO的 Type-C数据接口连接安卓系统手机。

2.开启手机“USB调试模式”，若有“OTG”选项也打开。

3.如手机自带的音乐播放器在使用XO过程中出现不稳定的情况，建议安装最新版海贝音乐播放器，在“设置”中打开“海贝独占USB输出”。

苹果系统手机、平板电脑的使用方法

1.通过官方定制的Type-C数据线与iPad连接后即可使用，免驱动。

2.如果需要支持苹果手机系统，请另行购买带苹果相机组件功能的Lightning转Type-C连接器。

Windows系统电脑的使用方法

1.通过USB数据线连接电脑。

2.无需安装驱动，即插即用。（不支持Windows 7及以下系统）

3.电脑设置：“控制面板”-“声音”-“播放”- 选择此产品（XO）为默认设备。

Mac OS系统电脑的使用方法

1.通过USB数据线连接Mac OS系统电脑。

2.电脑设置：“系统偏好设置”-“声音”-在选项中选择此产品为默认设备。

采样率指示灯

正面按键标志为“O”的位置为采样率指示灯。

粉：MQA　黄：DSD64/128/256

蓝：PCM176.4/192 (kHz)　红：PCM 352.8/384(kHz)

绿：PCM 44.1/48/88.2/96 (kHz)

实体按键

1.炫彩氛围灯：短按按键标志为“X”，支持多种以上灯光效果变化。

2.滤波切换：短按按键标志为“O”，支持2种滤波效果切换。

注意事项

* 请勿直接用力拉扯线材，以免线材变形或断裂。
* 拔插耳机线时应平行拔插，避免出现接口接触不良的现象。
* 请将耳机远离水，火，强磁场及儿童。
* 为了您的人身安全，请避免在危险的环境下使用耳机。
* 长时间不使用时，请将耳机拔出播放设备。
* 请调节音量至合适范围，以保护听力，请参考以下推荐使用。

（OSHA条例1910.95，dB:分贝；h:小时）

90dB	92dB	95dB	97dB	100dB	102dB	105dB	110dB	115dB
8h	6h	4h	3h	2h	1.5h	1h	0.5h	0.25h

保修条款

1.自购买之日起，主体保修期为12个月，线材保修期为6个月

2.维修时应提供有效的购买发票或购买凭证。

3.自购买之日起7日内，如产品本身出现质量问题，客户可在保持原厂包装、附件齐全且无损坏的情况下，享受包退换服务；

4.自购买之日起第8至15日，只可享受包换服务。

5.超过保修期我司会根据实际情况酌情收取维修费及元器件更换费用。

（运输费用：客户需承担将产品寄到Hidizs原厂的运费或者购买经销商。维修完毕后，产品将寄回给客户，此时运费由Hidizs或者购买经销商负责。）

以下情况不在保修范围内

a.自行拆解或未经授权维修产品。

b.非本公司及授权经销商出售的产品。

c.触水，跌落，撞击等引起的故障。

d.各种自然灾害引起的损坏。

e.其它非本公司造成的损坏。

f.无法提供有效保修凭证。

（若购买的产品出现质量问题，请联系相关经销商进行售后处理，或联系Hidizs官方客服以获得服务支持。）

技术支持及售后

1.关注Hidizs官方微博、Facebook、Instagram、Twitter、Tik Tok、Head-fi论坛、QQ交流群33504015和百度贴吧等，以获取更多信息并参与线上交流。

2.在官网的"联系我们"页面提交信息，以联系技术和售后部门。

3.官方售后邮箱：hello@hidizs.net

4.商务邮箱：Hidizs@hidizs.com

法律声明：版权所有Hidizs海帝思2022。保留一切权力

总代理：东莞市海帝思科技有限公司

地址：广东省东莞市常平镇木榆创业一路40号1栋101室

制造商：东莞市凯泰科技有限公司

地址：广东省东莞市常平镇木榆创业一路40号1栋101室

Dear user, thank you for purchasing Hidizs XO portable DAC amp, a small HiFi DAC amplifier certified by Hi-Res Audio and MQA.

XO has built-in 2 powerful ESS high-end SABER series latest-generation ESS9219C chips and a high-precision, low-jitter independent clock crystal oscillators, compatible with single-ended 3.5 and balanced 2.5 outputs, and supports local native hard decoding DSD64/128/256, with the highest PCM Support 32bit/384kHz, MQA supports up to 16X expansion, the power is strong but not excessive (balanced 195mW + 195mW@32Ω/single-ended: 78mW+78mW@32Ω), supports iOS, Android, Windows, Mac OS, iPad OS, plug and play.

The independent button "XO" has the function of filter switching and colorful ambient light. There are a variety of above-mentioned lights to choose from, and 2 kinds of filter effects can be switched. You can experience different sound styles without flashing the firmware, adding fun to your HiFi trip . XO has been precisely tuned by the Hidizs audio team, and the hearing adjustment is delicate and subtle to ensure pure and transparent sound quality, hoping to bring you a pleasant experience.

You Are Invited to Subscribe for Hidizs Membership!

Sign up and get a coupon. You will receive the latest Hidizs news, coming deals, promotions, giveaways and various internal member events in advance.

Scan the QR code or visit www.hidizs.net/pages/vip to become a member of Hidizs.

Subscribe for Hidizs membership

For more information about Hidizs, please follow our official website, Facebook, Instagram, TikTok, Twitter and Weibo.

Hidizs official website: www.hidizs.com OR www.hidizs.net.

Facebook Twitter Instagram TikTok Weibo

User Manual

Android User Guide

1.Connect Android phone via the Type-C data port of XO dongle.

2. Turn on the “USB debugging mode" of the phone, and the “OTG" option(if there is).

3.It is recommended to install the latest version of HiBy Music Player and turn on "HiBy Exclusive USB Output" in "Settings", if the phone's self-contained music player is unstable while using with the XO.

iPhone & iPad User Guide

1.Connect iPad through Hidizs customized Type-C cable.

2. Please note: the Lightning to Type-C cable with OTG function has to be purchased separately to support iOS.

Windows PC User Guide

1.Connect computer through the USB cable.

2. No need to install drivers, plug and play.

(Windows 7 and earlier versions are unsupported)

3. PC settings: “Control panel" - “Sound" - “Playback" - select this product(XO) as the default device.

Mac OS PC User Guide

1.Connect Mac OS PC through the USB cable.

2.PC settings: “System preferences" - “Sound" - select this product as the default device.

Sampling Rate Indicator Light

The front button "O" is the sampling rate indicator

Pink: MQA　Yellow: DSD 64/128/256

Blue: PCM 176.4/192 (kHz)　Red: PCM 352.8/384 (kHz)

Green: PCM 44.1/48/88.2/96 (kHz)

Physical Button

1. Colorful ambient light: Short press the "X" button to switch various lighting effects.

2. Filter switching: Short press the "O" button to switch between 2 filter effects.

Precautions

* Please do not pull the cable strongly to avoid damage.
* When inserting or removing cable, be sure to push or pull in direct line. Any force applied in other directions will cause damage to connectors or earphone's sockets.
* Please keep the earphones away from fire, damp, strong magnetic field and children.
* For your safety, please do not use earphones in dangerous environment.
* If unused for a long time, please unplug your earphones from the playback device.
* Please set the volume to a suitable level to avoid hearing damage. Refer to the following chart.(dB: volume, h: time)

90dB	92dB	95dB	97dB	100dB	102dB	105dB	110dB	115dB
8h	6h	4h	3h	2h	1.5h	1h	0.5h	0.25h

Warranty

1. From the date of purchase, the earphone units are under warranty for twelve months and cables are six months.

2. Please provide a valid purchase invoice or proof of purchase when applying for warranty repair.

3. If any malfunction is caused by quality related problems within 7 days from the date of purchase, as well as the original packaging and all accessories were kept without damage, customer can apply for replacement or refund within 7 days from purchase.

4. Between 8th and 15th day from purchase, customer can apply for replacement only.

5. Repairs will be charged when out of warranty.

Shipping fees: the customer pays for the shipping cost of sending the product to Hidizs factory or dealer. After it' s repaired, the product will be sent back to the customer, the shipping cost is paid by Hidizs or dealer.

This Warranty Does Not Apply:

a. Unauthorized disassembly or repair of the product.

b. The products are not sold by Hidizs or Hidizs authorized distributors.

c. Damage caused by water, drop, crash and others.

d. Damage caused by natural disasters.

e. Other damage caused by third-party-company.

f. Fail to provide valid warranty proofs.

(If product has quality issues, please contact the seller for after-sales service, or contact Hidizs (hello@hidizs.net) for service support.)

Technical Support & After-Sales Service

1. Follow our Weibo, Facebook, Instagram, Twitter, TikTok, Head-fi forum, QQ group(33504015) and Baidu Post for more information and after-sales service.

2. Fill in information in "Contact Us" on Hidizs official website to contact the Customer Services.

3. Official after-sales email: hello@hidizs.net

4. Business email: Hidizs@hidizs.com

Copyright © Hidizs Technology Co., Ltd. 2022. All rights reserved.

General agent: Hidizs Technology Co., Ltd.

Address: Room 101, Building 40-1, Chuangye 1st Road, Changping Town, Dongguan City, Guangdong Province, China.

Manufacturer: Hidizs Technology Co., Ltd.

Address: Room 101, Building 40-1, Chuangye 1st Road, Changping Town, Dongguan City, Guangdong Province, China.

Hidizs XO をご購入いただきありがとうございます。本製品は Hi-Res・MQA 二重認証を取る小型アンプです。

XO アンプは ESS9219C DAC チップをデュアルで搭載しています。SABRE シリーズの最新チップセットで、更に高精度の独立水晶発振器を搭載しており、シングルエンド 3.5 ㎜・バランス 2.5 ㎜に対応し、ネイティブ DSD64/128/256 に対応できます。また、PCM は最大 32bit ／ 384kHz まで拡張可能になり、MQA は最大 16X まで対応します。十分な駆動力があります（195mW+195mW@32Ωバランス／ 78mW+78mW@Ωシングルエンド）。IOS、Android、Windows、Mac OS、iPad OS システムに対応できます。

「XO」ボタンは、2 種類のフィルター変換と RGB LED 呼吸灯に対応します。一方、Hidizs XO はプロのオーディオチームによるチューニングされたので、クリーンなサウンドを再生して最大限に楽しむことができます。

Hidizs VIP になるよう心からご招待致します。

サインアップしてクーポンを取得できます。Hidizs に関する新製品のプロモーション、giveaway、クーポン券など、さまざまな情報をお受け取ります。

下記の QR コードをスキャンすると、VIP になります。

Subscribe for Hidizs membership

より多くの情報をお手に入る場合は、次の公式アカウントをフォローしてください：Facebook、Instagram、Twitter、TikTok、Weibo

Hidizs公式サイト：www.hidizs.com / www.hidizs.net

Facebook Twitter Instagram TikTok Weibo

ユーザーガイド

Android ユーザーガイド

1、スマホを「Hidizs XO」の type-c ポートに接続します。

2、スマホの「USB デバッグモード」をオンにします。「OTG」オプションがある場合、それもオンにしてください。

3、XO と接続してから、スマホに付属の音楽プレーヤーが不安定になれば、最新版の HiBy APP をインストールしてください。そして、XO の「設定」で、「HiBy 専用 USB 出力」をオンにします。

iPhone & iPad ユーザーガイド

1、Hidizs カスタムの type-c ケーブルを iPad に接続してから使用できます。

2、備考：IOS の場合は、Lightning to Type-C 機能を備えたコネクターを別途購入してください。

Windows PC ユーザーガイド

1、USB ケーブルを PC に接続してください

2、ドライバをインストールする必要はありません。接続すると使用できます。(Windows 7 及びその以下のシステムに対応できない)

3、PC 設定：「コントロールパネル」-「サウンド」-「再生」-「Hidizs XO」をデフォルトのデバイスを選択してください。

Mac OS PC ユーザーガイド

1、USB ケーブルを Mac OS PC に接続してください。

2、PC 設定：「システム環境設定」-「サウンド」-本製品をデフォルトのデバイスを選択してください。

サンプリングレートインディケータライト

正面にある「O」型ボタンはサンプリングレートインディケータです。

Pink: MQA　Yellow: DSD 64/128/256

Blue: PCM 176.4/192 (kHz)　Red: PCM 352.8/384 (kHz)

Green: PCM 44.1/48/88.2/96 (kHz)

物理ボタン

1、RGB イルミネーション：「X」型ボタンを短く押すと、たくさんのイルミネーション変更に対応します。

2、フィルタ変換：「O」型ボタンを短く押すと、2 種類のフィルタ変換に対応します。

注意事項

* 線材をぐんと引っ張らないでください。線材が変形、破断になる可能で、USB ポートも壊れるかもしれません。
* ポートが接触不良にならないために、イヤホンケーブルを水平に抜き出すか挿入するかを確認してください。
* 製品を水、火、強い磁場や子供たちから遠ざけてください。
* 個人安全のために、危険な環境での使用を避けてください。
* 長時間使用しない場合は、イヤホンを再生デバイスから抜き取ってください。
* 聴覚を保護するために、適切な範囲に音量を調整してください。以下のを参考までに。(dB：ボリューム；h：時間)

90dB	92dB	95dB	97dB	100dB	102dB	105dB	110dB	115dB
8h	6h	4h	3h	2h	1.5h	1h	0.5h	0.25h

保証アイテム

1. 購入日以降、本体保証期間は１２ヶ月、線材のは6ヶ月です。

2. 修理する際には、有効的な領収書または証票を提出必要があります。

3. 購入日から七日以内、製品が初期不良で、オリジナルの包装及び付属品が損傷のない状態を前提として、返品交換サービスが提供できます。

4. 購入日から8～１５日まで、交換サービスだけ提供できません。

5. 保証期間終了後、弊社は実際の状況により修理代と部品の交換費用を請求させていただきます。

（運送費について：お客さんが Hidizs 原産地またはディーラーに不良品を返送する費用を担当お願いいたします。修理完了したら、当社またはディーラーは修理品を返送して、運送費を担当いたします。）

次の条件は保証の対象外です

a. 許可なく製品を分解または修理します。

b. 当社および正規販売代理店が授権のない販売している製品。

c. 水との接触、落下、衝撃などによる故障。

d. 自然災害による損害。

e. 当社以外の損害。

f. 有効な保障材料を提出できません。

（ご購入した製品に欠陥がある場合は、関連のセーラにお問い合わせください。或いは、Hidizs に直接問い合わせください。(hello@hidizs.net)

技術サポート&アフターサービス

1. 詳細情報とオンライン通信のために、Hidizs の公式 Weibo、Facebook、Instagram、Twitter、Tik Tok、Head-fifi フォーラム、QQ グループ(33504015)や Baidu Post をご利用いただけます。

2. テクニックサポートとアフターサービスのために、公式サイトでの「お問い合わせ」までご連絡ください。

3. アフターサービスに関する：hello@hidizs.net までご連絡ください。

4. ビジネスに関する：Hidizs@hidizs.com までご連絡ください。

Copyright © Hidizs Technology Co., Ltd. 2022. All rights reserved.

General agent: Hidizs Technology Co., Ltd.

Address: Room 101, Building 40-1, Chuangye 1st Road, Changping Town, Dongguan City, Guangdong Province, China.

Manufacturer: Hidizs Technology Co., Ltd.

Address: Room 101, Building 40-1, Chuangye 1st Road, Changping Town, Dongguan City, Guangdong Province, China.